

NE77-THB5

NE77/P2/P5 DIP SWITCHES SETTING : (Pulse/ICT)

Supported bill THB 20, 50, 100, 500, 1000 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / THB 10	OFF	OFF								
	2 Pulse / THB 10	OFF	ON								
	5 Pulse / THB 10	ON	OFF								
	10 Pulse / THB 10	ON	ON								
	Fast output Pulse Lo= 50ms Hi=100ms			ON							
★	Slow output Pulse Lo= 50ms Hi=300ms			OFF							
★	Inhibit level Active Low				ON						
	Inhibit level Active High				OFF						
★	Accept THB 20 & 50					ON					
	Reject THB 20 & 50					OFF					
★	Accept THB 100						ON				
	Reject THB 100						OFF				
★	Accept THB 500 & 1000							ON			
	Reject THB 500 & 1000							OFF			
★	Pluse Normal High								ON		
	Pluse Normal Low								OFF		
★	Pulse Mode									ON	
	ICT Mode									OFF	
★	Manufacture Default										ON
	System Default										OFF

(★) Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT
BV1	THB 20	THB 20
BV2	THB 50	THB 50
BV3	THB 100	THB 100
BV4	THB 500	THB 500
BV5	THB 1000	THB 1000