

NE77-USD6

NE77 DIP SWITCHES SETTING : (Pulse/Parallel A4)

Supported bill USD 1, 5, 10, 20, 50, 100 6bills.

DIP SWITCHES SETTING : (Parallel A4)

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10	
★	With Escow Function	ON										
	No Escow Function	OFF										
	Reserved		ON									
★	Reserved		OFF									
	Reserved			ON								
★	Reserved			OFF								
★	Enable Output Sensor Detect (★★)				ON							
	Disable Output Sensor Detect (★★)				OFF							
	Reserved					ON						
★	Reserved					OFF						
	Optical anti-fishing malfunction, BA will be still in working order (★★★)						ON					
★	BA will stop to work when it acknowledges Optical anti-fishing malfunction (★★★)						OFF					
★	Accept USD \$1 & 5 & 10 & 20							ON				
	Reject USD \$1 & 5 & 10 & 20							OFF				
★	Accept USD \$50 & 100								ON			
	Reject USD \$50 & 100								OFF			
	Disable Bill Reject 4 Times BA Stop By 30 Sec										ON	
★	Enable Bill Reject 4 Times BA Stop By 30 Sec										OFF	
	Pulse Protocol											ON
★	Parallel A4 Protocol											OFF

★ Manufacture setting

★★ ON: Autocheck motor reversal.

OFF: When output or hook is triggered in power on, error message displays three red, until after trouble clearing into autocheck.

★★★ ON: (1) After accepted banknotes through output sensor, if detect output trigger again, display sensor problem.

(2) After accepted banknote didn't leave output sensor, display sensor problem.

OFF: (1) After accepted banknotes through output sensor, if detect output trigger again, display sensor problem.

(2) After accepted banknote didn't leave output sensor, return to the idle.

Note: Please restart the bill acceptor after any changes on dip switch(s) has been made.

Appendix

NE77 - USD6 (Pulse/Parallel A4)

DIP SWITCHES SETTING : (Pulse)

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
	5 Pulses / USD \$1	ON									
★	1 Pulse / USD \$1	OFF									
★	Lo=150ms / Hi=180ms										
	Lo= 50ms / Hi= 50ms		OFF	OFF							
	Lo= 80ms / Hi=120ms		ON	OFF							
	Lo= 50ms / Hi=300ms		ON	ON							
★	Enable Output Sensor Detect (★★)				ON						
	Disable Output Sensor Detect (★★)				OFF						
	Inhibit level Active High					ON					
★	Inhibit level Active Low					OFF					
	Optical anti-fishing malfunction, BA will be still in working order (★★★)										
★	BA will stop to work when it acknowledges Optical anti-fishing malfunction (★★★)										
★	Accept USD \$1 & 5 & 10 & 20							ON			
	Reject USD \$1 & 5 & 10 & 20							OFF			
★	Accept USD \$50 & 100										
	Reject USD \$50 & 100								ON		
★	Disable Bill Reject 4 Times BA Stop By 30 Sec										
★	Enable Bill Reject 4 Times BA Stop By 30 Sec										
	Pulse Protocol										ON
	Parallel A4 Protocol										OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	Parallel A4
BV1	USD 1	USD 1
BV2	USD 5	USD 5
BV3	USD 10	USD 10
BV4	USD 20	USD 20
BV5	USD 50	USD 50
BV6	USD 100	USD 100