

NK682-MYR4

NK682 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill MYR 1, 5, 10, 20 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10	
★	1 Pulse / MYR 1	OFF	OFF									
	5 Pulse / MYR 1	ON	OFF									
	10 Pulse / MYR 1	OFF	ON									
	20 Pulse / MYR 1	ON	ON									
★	Accept MYR 1			ON								
	Reject MYR 1			OFF								
★	Accept MYR 5				ON							
	Reject MYR 5				OFF							
★	Accept MYR 10					ON						
	Reject MYR 10					OFF						
★	Accept MYR 20						ON					
	Reject MYR 20						OFF					
★	Enable Output Sensor Detect								ON			
	Disable Output Sensor Detect								OFF			
★	Fast output Pulse Lo= 50ms Hi=100ms								ON			
	Slow output Pulse Lo=100ms Hi=200ms								OFF			
★	Pulse Mode									ON		
	ICT104U Mode									OFF		
	Manufacture Default										ON	
★	System Default										OFF	

(★) Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	Pulse
BV1	MYR 1	MYR 1
BV3	MYR 5	MYR 5
BV4	MYR 10	MYR 10
BV5	MYR 20	MYR 20