

NK77-KHR9

NK77 DIP SWITCHES SETTING : (Pulse/Out of Service/ICT104U)

Supported bill KHR 100, 500, 1000, 2000, 5000, 10000, 20000, 50000, 100000 9bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / KHR 100	OFF	OFF								
	2 Pulse / KHR 100	OFF	ON								
	5 Pulse / KHR 100	ON	OFF								
	10 Pulse / KHR 100	ON	ON								
	Enable Fish Stop			ON							
★	Disable Fish Stop			OFF							
★	Inhibit level Active Low				ON						
	Inhibit level Active High				OFF						
★	Accept KHR 100 & 500 & 1000 & 2000 & 5000 & 10000					ON					
	Reject KHR 100 & 500 & 1000 & 2000 & 5000 & 10000					OFF					
★	Accept KHR 20000 & 50000 & 100000						ON				
	Reject KHR 20000 & 50000 & 100000						OFF				
	Enable Output Sensor Detect							ON			
★	Disable Output Sensor Detect							OFF			
★	Pulse Normal High								ON		
	Pulse Normal Low								OFF		
★	Pulse Mode									ON	
	ICT104U Mode									OFF	
★	Power On Motor Plus										ON
	Power On Motor Minus										OFF

(★) Manufacture setting

Note:1. Please reset the bill acceptor after set the dip switch

2. Pulse mode has out of service function
3. Out of service:Normal High,Error Low
4. Pulse speed is LO=50ms/HI=100ms

Currency Assign Data

Interface Bill value	ICT104U	Pulse
BV1	KHR 100	KHR 100
BV2	KHR 500	KHR 500
BV3	KHR 1000	KHR 1000
BV4	KHR 2000	KHR 2000
BV5	KHR 5000	KHR 5000
BV6	KHR 10000	KHR 10000
BV7	KHR 20000	KHR 20000
BV8	KHR 50000	KHR 50000
BV9	KHR 100000	KHR 100000