

NK77-THB5

NK77 DIP SWITCHES SETTING : 1(Pulse/ICT104V)

Supported bill THB 20, 50, 100, 500, 1000 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / THB 10	OFF	OFF								
	2 Pulses / THB 10	OFF	ON								
	5 Pulses / THB 10	ON	OFF								
	10 Pulses / THB 10	ON	ON								
	Enable Fish Stop			ON							
★	Disable Fish Stop			OFF							
★	Inhibit level Active Low				ON						
	Inhibit level Active High				OFF						
★	Accept THB 20 & 50 & 100					ON					
	Reject THB 20 & 50 & 100					OFF					
★	Accept THB 500 & 1000						ON				
	Reject THB 500 & 1000						OFF				
	Enable Output Sensor Detect							ON			
★	Disable Output Sensor Detect							OFF			
★	Pulse Normal High								ON		
	Pulse Normal Low								OFF		
★	Pulse Mode									ON	
	ICT104V Mode									OFF	
★	Power On Motor Plus										ON
	Power On Motor Minus										OFF

(★) Manufacture setting

Note : 1. Please reset the bill acceptor after set the dip switch

2. Pulse mode has out of service function
3. Out of service:Normal High,Error Low
4. Pulse speed is LO=50ms/HI=100ms

Currency Assign Data

Interface Bill value	ICT104V	Pulse
BV1	THB 20	THB 20
BV2	THB 50	THB 50
BV3	THB 100	THB 100
BV4	THB 500	THB 500
BV5	THB 1000	THB 1000

Appendix