

S7A II-HUF6 Option Switch Settings (Pulse/MDB/ICT104U/Parallel A3)

Supported bill Ft 500, 1000, 2000, 5000, 10000, 20000 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
	Reject Ft 500 & 1000	ON											
★	Accept Ft 500 & 1000	OFF											
	Reject Ft 2000		ON										
★	Accept Ft 2000		OFF										
	Reject Ft 5000			ON									
★	Accept Ft 5000			OFF									
	Reject Ft 10000 & 20000				ON								
★	Accept Ft 10000 & 20000				OFF								
	Reserved				ON								
★	Reserved				OFF								
	Disable Bill Reject 4 Times BA Stop By 30 Sec					ON							
★	Enable Bill Reject 4 Times BA Stop By 30 Sec					OFF							
	Stack Banknote when Power-up						ON						
★	Reject Banknote when Power-up						OFF						
	Other Interface	Test Mode (No Communication)							ON				
★		Operation Mode							OFF				
	Pulse Mode	Inhibit Active HIGH (Test)							ON				
★		Inhibit Active LOW							OFF				
	ENABLE IrDA Download								ON				
★	Reserved								OFF				
	ENABLE INHIBIT-Sleep only									ON			
★	5 second Timeout only									OFF			
	Normal (Note.2)										OFF	OFF	
	Mode 1 (Note.3)										OFF	ON	
	Mode 2 (Note.4)										ON	OFF	
★	Mode 1 + 2 (Note.5)										ON	ON	

Note: 1. After setting dip switch of the credit pulses, you should reset the bill acceptor again.

2. Normal : No sleep function.

3. Mode 1 : Bill-acceptor wakes up VMC with banknote only (special cable required).

4. Mode 2 : VMC wakes up bill-acceptor.

5. Mode 1+2 : Bill-acceptor wakes up with banknote or by VMC.

Appendix

S7A II-HUF6(Pulse/MDB/ICT104U/Parallel A3)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	Other Mode		OFF		
★	1 pulse / Ft 500			OFF	OFF
	5 pulses / Ft 500			OFF	ON
	10 pulses / Ft 500			ON	OFF
	25 pulses / Ft 500			ON	ON

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB			OFF	OFF
★	ICT104U			OFF	ON
	Reserved			ON	ON
	Parallel A3			ON	OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
★	MDB			OFF	OFF
	ICT104U			OFF	ON
	Reserved			ON	ON
	Parallel A3			ON	OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(Parallel A3)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Other Mode		OFF		
	MDB			OFF	OFF
	ICT104U			OFF	ON
	Reserved			ON	ON
★	Parallel A3			ON	OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U	Parallel A3
BV1	Ft 500	Ft 500	Ft 500	Ft 500
BV2	Ft 1000	Ft 1000	Ft 1000	Ft 1000
BV3	Ft 2000	Ft 2000	Ft 2000	Ft 2000
BV4	Ft 5000	Ft 5000	Ft 5000	Ft 5000
BV5	Ft 10000	Ft 10000	Ft 10000	
BV6	Ft 20000	Ft 20000	Ft 20000	