S7A II-TRY6 Option Switch Settings (Pulse/MDB/ICT/Parallel A3)Supported bill Lira 5, 10, 20, 50, 100, 200 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
	Reject Lira 5 & 10	ON											
*	Accept Lira 5 & 10	OFF											
	Reject Lira 20		ON										
*	Accept Lira 20		OFF										
	Reject Lira 50			ON									
*	Accept Lira 50			OFF									
	Reject Lira 100 & 200				ON								
*	Accept Lira 100 & 200				OFF								
	Reserved					ON							
*	Reserved					OFF							
	Disable Bill Reject 4 Times BA Stop By 30 Sec						ON						
*	Enable Bill Reject 4 Times BA Stop By 30 Sec	OFF											
	Stack Banknote when Power-up	ON											
*	Reject Banknote when Power-up	OFF											
	Other Interface		Test Mode (No Communication)										
*			Operation Mode OFF										
	Pulse Mode		Inhibit Active HIGH (Test)										
*	i dise Mode	Inhibit Active LOW						OFF					
	ENABLE IrDA Download	ON											
*	Reserved									OFF			
	Reserved										ON		
*	Reserved	OFF											
	Reserved	Reserved ON											
*	Reserved	Reserved OFF											
	Reserved								ON				
*	Reserved												OFF

[★] Manufacture setting

Note: After setting dip switch of the credit pulses, you should reset the bill acceptor again.

_____Appendix

S7A II-TRY6(Pulse/MDB/ICT/Parallel A3)

DIP SWITCHES SETTING: 3(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4	
*	Credit-Pulse Normal High	ON				
	Credit-Pulse Normal Low	OFF				
*	Pulse Mode		ON			
	Other Mode		OFF			
*	1 pulse / Lira 5			OFF	OFF	
	5 pulses / Lira 5			OFF	ON	
	10 pulses / Lira 5			ON	OFF	
	25 pulses / Lira 5			ON	ON	

[★] Manufacture setting

DIP SWITCHES SETTING: 3(Other)

	FUNCTION	SW1	SW2	SW3	SW4
*	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
*	Other Mode		OFF		
*	MDB			OFF	OFF
	ICT			OFF	ON
	Reserved			ON	ON
	Parallel A3			ON	OFF

[★] Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB	ICT	Parallel A3		
BV1	Lira 5	Lira 5	Lira 5	Lira 5		
BV2	Lira 10	Lira 10	Lira 10	Lira 10		
BV3	Lira 20	Lira 20	Lira 20	Lira 20		
BV4	Lira 50	Lira 50	Lira 50	Lira 50		
BV5	Lira 100	Lira 100	Lira 100			
BV6	Lira 200	Lira 200	Lira 200			