

S7ER-THB4 Option Switch Settings: (Pulse)

Supported bill THB 20, 50, 100, 500 4bills.

S7ER dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4	SW1	SW2	SW3	SW4
Reject THB 20	ON															
★ Accept THB 20	OFF															
Reject THB 50		ON														
★ Accept THB 50		OFF														
Reject THB 100			ON													
★ Accept THB 100			OFF													
Reject THB 500				ON												
★ Accept THB 500				OFF												
High Acceptance					ON											
★ High Security(*)					OFF											
Reserved					ON											
★ Reserved					OFF											
Reserved						ON										
★ Reserved						OFF										
Reserved							ON									
★ Reserved							OFF									
Inhibit Active HIGH								ON								
★ Inhibit Active LOW								OFF								
★ Pulse Speed	100ms HI / 100ms LO							ON								
	50ms HI / 50ms LO							OFF								
Reserved									ON							
★ Reserved									OFF							
Reserved										ON						
★ Reserved										OFF						
Reserved											ON					
★ Reserved											OFF					
Reserved												ON				
★ Reserved												OFF				
★ Credit-Pulse Normal HIGH										ON						
Credit-Pulse Normal LOW											OFF					
★ Pulse Mode												ON				
★ ICT104U Mode												OFF				
★ 1 pulse / THB 10													OFF		OFF	
5 pulses / THB 10														OFF	ON	
10 pulses / THB 10															ON	OFF
25 pulses / THB 10															ON	ON

★ Manufacture setting

Note1. After setting dip switch of the credit pulses,you should reset the bill acceptor again.

Note2. High Security mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

S7ER-THB4 (ICT104U)

S7ER dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4	SW1	SW2	SW3	SW4
Reject THB 20	ON															
★ Accept THB 20	OFF															
Reject THB 50		ON														
★ Accept THB 50		OFF														
Reject THB 100			ON													
★ Accept THB 100			OFF													
Reject THB 500				ON												
★ Accept THB 500				OFF												
High Acceptance					ON											
★ High Security(*)					OFF											
Reserved						ON										
★ Reserved						OFF										
Reserved							ON									
★ Reserved							OFF									
Reserved								ON								
★ Test Mode								OFF								
★ Reserved									ON							
Reserved										ON						
★ Reserved										OFF						
Reserved											ON					
★ Reserved											OFF					
Reserved												ON				
★ Reserved												OFF				
Reserved													ON			
★ Reserved													OFF			
Pulse Mode														ON		
★ ICT104U Mode															OFF	
Reserved															ON	
★ Reserved															OFF	
Reserved																ON
★ Reserved																OFF

★ Manufacture setting

Note1. After setting dip switch of the credit pulses,you should reset the bill acceptor again.

Note2. High Security mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

Currency Assign Data

Interface	ICT104U	Pulse
BV1	THB 20	THB 20
BV2	THB 50	THB 50
BV3	THB 100	THB 100
BV4	THB 500	THB 500