

A7-RUB5

A7 Option Switch Settings: 1 (Pulse/ICT)

Supported bill Ruble 10, 50, 100, 500, 1000 5bills.

A7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject Ruble 10	ON											
★	Accept Ruble 10	OFF											
★	Reject Ruble 50		ON										
★	Accept Ruble 50		OFF										
★	Reject Ruble 100			ON									
★	Accept Ruble 100			OFF									
★	Reject Ruble 500				ON								
★	Accept Ruble 500				OFF								
★	Reject Ruble 1000					ON							
★	Accept Ruble 1000					OFF							
★	Reserved					ON							
★	Reserved					OFF							
★	Harness Disable						ON						
★	Harness Enable						OFF						
★	Inhibit Active High							ON					
★	Inhibit Active Low							OFF					
★	10 pulse / Ruble 10								OFF	OFF			
	20 pulse / Ruble 10								ON	OFF			
	50 pulse / Ruble 10								OFF	ON			
	100 pulse / Ruble 10								ON	ON			
★	Pulse Speed	50ms on / 50ms off										OFF	OFF
		60ms on / 300ms off										ON	OFF
		30ms on / 50ms off										OFF	ON
		150ms on / 150ms off										ON	ON

◆ Factory configuration has all switches in the OFF position.

Note : (1) Please reset the bill acceptor after any changes on Dip switch.

(2) SW6 . SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

A7-RUB5

A7 Interface Settings: 2 (ICT)

	INTERFACE	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	ICT Interface		OFF		
★	Reserved			ON	
★				OFF	
					ON
★					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT	Pulse
BV1	Ruble 10	Ruble 10
BV2	Ruble 50	Ruble 50
BV3	Ruble 100	Ruble 100
BV4	Ruble 500	Ruble 500
BV5	Ruble 1000	Ruble 1000