

L70/L70F-AUD5

L70/L70F/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill \$A 5, 10, 20, 50, 100 5 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / \$A 5	OFF	OFF	OFF							
	2 Pulse / \$A 5	OFF	OFF	ON							
	3 Pulse / \$A 5	OFF	ON	OFF							
	4 Pulse / \$A 5	OFF	ON	ON							
	5 Pulse / \$A 5	ON	OFF	OFF							
	6 Pulse / \$A 5	ON	OFF	ON							
	10 Pulse / \$A 5	ON	ON	OFF							
	20 Pulse / \$A 5	ON	ON	ON							
	Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★	Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept \$A 5 & 10				ON						
★	Reject \$A 5 & 10				OFF						
★	Accept \$A 20				ON						
	Reject \$A 20				OFF						
★	Accept \$A 50				ON						
	Reject \$A 50				OFF						
★	Accept \$A 100				ON						
	Reject \$A 100				OFF						
★	High Security <small>(Note.3)</small>				ON						
	High Acceptance				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

(3)High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit - Pulse Normal High	ON			
	Credit - Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	ICT104U Mode		OFF		
★	Reserved			ON	
				OFF	
				ON	
★				OFF	

Currency Assign Data

Interface Bill value	ICT104U	Pulse
BV1	5	5
BV2	10	10
BV3	20	20
BV4	50	50
BV5	100	100