

CAD5

L70/P5 DIP SWITCHES SETTING : 1(ICT/Pulse)

Supported bill Can\$ 5, 10, 20, 50, 100 5bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / Can\$ 5	OFF	OFF	OFF							
2 Pulse / Can\$ 5	OFF	OFF	ON							
3 Pulse / Can\$ 5	OFF	ON	OFF							
4 Pulse / Can\$ 5	OFF	ON	ON							
5 Pulse / Can\$ 5	ON	OFF	OFF							
10 Pulse / Can\$ 5	ON	OFF	ON							
20 Pulse / Can\$ 5	ON	ON	OFF							
100 Pulse / Can\$ 5	ON	ON	ON							
Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
Inhibit level Active Low					ON					
Inhibit level Active High					OFF					
★ Accept Can\$ 5						ON				
Reject Can\$ 5						OFF				
★ Accept Can\$ 10							ON			
Reject Can\$ 10							OFF			
★ Accept Can\$ 20								ON		
Reject Can\$ 20								OFF		
★ Accept Can\$ 50									ON	
Reject Can\$ 50									OFF	
★ Accept Can\$ 100										ON
Reject Can\$ 100										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.
 (2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

FUNCTION	SW1	SW2	SW3	SW4
★ Credit - Pulse Normal High	ON			
Credit - Pulse Normal Low	OFF			
★ Pulse Mode		ON		
ICT Mode		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

Currency Assign Data

Interface Bill value	ICT	Pulse
BV1	Can\$ 5	Can\$ 5
BV2	Can\$ 10	Can\$ 10
BV3	Can\$ 20	Can\$ 20
BV4	Can\$ 50	Can\$ 50
BV5	Can\$ 100	Can\$ 100