



EUR2

L70/P5 DIP SWITCHES SETTING : 1 (ICT/Pulse)

Supported bill Euro 5, 10 2bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / Euro 5	OFF	OFF	OFF							
	2 Pulse / Euro 5	OFF	OFF	ON							
	3 Pulse / Euro 5	OFF	ON	OFF							
	4 Pulse / Euro 5	OFF	ON	ON							
	5 Pulse / Euro 5	ON	OFF	OFF							
	10 Pulse / Euro 5	ON	OFF	ON							
	20 Pulse / Euro 5	ON	ON	OFF							
	100 Pulse / Euro 5	ON	ON	ON							
	Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★	Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept Euro 5					ON					
	Reject Euro 5					OFF					
★	Accept Euro 10						ON				
	Reject Euro 10						OFF				
	Reserved								ON		
★	Reserved								OFF		
	Reserved									ON	
★	Reserved									OFF	
	Reserved										ON
★	Reserved										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit - Pulse Normal High	ON			
	Credit - Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	ICT Mode		OFF		
★	Reserved			ON	
				OFF	
	Reserved				ON
★					OFF

