

## EUR2

### L70/P5 DIP SWITCHES SETTING : 1(Pulse/M.D.B)

Supported bill € 5, 10 2bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / € 5	OFF	OFF	OFF							
2 Pulse / € 5	OFF	OFF	ON							
3 Pulse / € 5	OFF	ON	OFF							
4 Pulse / € 5	OFF	ON	ON							
5 Pulse / € 5	ON	OFF	OFF							
10 Pulse / € 5	ON	OFF	ON							
20 Pulse / € 5	ON	ON	OFF							
100 Pulse / € 5	ON	ON	ON							
Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept € 5						ON				
Reject € 5						OFF				
★ Accept € 10							ON			
Reject € 10							OFF			
Reserved								ON		
★ Reserved								OFF		
Reserved									ON	
★ Reserved									OFF	
Reserved										ON
★ Reserved										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.  
(2) Dip switches 1 to 5 are only used for pulse protocol.

## L70-EUR2/P5(Pulse/M.D.B)

### DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON		
M.D.B Interface		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

★ Manufacture setting

### DIP SWITCHES SETTING : 3(M.D.B)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
★ Pulse Mode		ON		
M.D.B Interface		OFF		
★ Reserved			ON	
			OFF	
				ON
				OFF

★ Manufacture setting

### Currency Assign Data

Interface Bill value	Pulse	M.D.B
BV1	€ 5	€ 5
BV2	€ 10	€ 10