



IDR3

L70/P5 DIP SWITCHES SETTING : 1(ICT/Pulse)

Supported bill Rp 1000, 5000, 10000

3 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / Rp 1000	OFF	OFF	OFF							
	2 Pulse / Rp 1000	OFF	OFF	ON							
	3 Pulse / Rp 1000	OFF	ON	OFF							
	4 Pulse / Rp 1000	OFF	ON	ON							
	5 Pulse / Rp 1000	ON	OFF	OFF							
	10 Pulse / Rp 1000	ON	OFF	ON							
	20 Pulse / Rp 1000	ON	ON	OFF							
	100 Pulse / Rp 1000	ON	ON	ON							
	Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★	Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept Rp 1000				ON						
	Reject Rp 1000				OFF						
★	Accept Rp 5000				ON						
	Reject Rp 5000				OFF						
★	Accept Rp 10000				ON						
	Reject Rp 10000				OFF						
	Reserved					ON					
★	Reserved					OFF					
	Reserved						ON				
★	Reserved						OFF				

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit - Pulse Normal High	ON			
	Credit - Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	ICT Mode		OFF		
★	Reserved			ON	
				OFF	
				ON	
★				OFF	

