

L70-MMK6

L70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT)

Supported bill MMK 100, 200, 500, 1000, 5000, 10000 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / MMK 100	OFF	OFF	OFF							
	2 Pulse / MMK 100	OFF	OFF	ON							
	3 Pulse / MMK 100	OFF	ON	OFF							
	4 Pulse / MMK 100	OFF	ON	ON							
	5 Pulse / MMK 100	ON	OFF	OFF							
	10 Pulse / MMK 100	ON	OFF	ON							
	20 Pulse / MMK 100	ON	ON	OFF							
	100 Pulse / MMK 100	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept MMK 100 & 200				ON						
	Reject MMK 100 & 200				OFF						
★	Accept MMK 500				ON						
	Reject MMK 500				OFF						
★	Accept MMK 1000				ON						
	Reject MMK 1000				OFF						
★	Accept MMK 5000				ON						
	Reject MMK 5000				OFF						
★	Accept MMK 10000				ON						
	Reject MMK 10000				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L70-MMK6/P5(Pulse/ICT)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	ICT104U Interface		OFF		
★	Reserved			ON	
				OFF	
★				ON	
				OFF	

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
★	Pulse Mode		ON		
	ICT104U Interface		OFF		
★	Reserved			ON	
				OFF	
★				ON	
				OFF	

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT	Pulse
BV1	MMK 100	MMK 100
BV2	MMK 200	MMK 200
BV3	MMK 500	MMK 500
BV4	MMK 1000	MMK 1000
BV5	MMK 5000	MMK 5000
BV6	MMK 10000	MMK 10000