

## L70-NIO3+USD1

### L70/P5 DIP SWITCHES SETTING : 1(ICT104U)

Supported bill NIO 100, 500, 1000 3 bills.  
USD 20 1 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	Reserved	ON									
★	Reserved	OFF									
★	Reserved		ON								
★	Reserved		OFF								
★	Reserved			ON							
★	Reserved			OFF							
★	Reserved				ON						
★	Reserved				OFF						
★	Reserved					ON					
★	Reserved					OFF					
★	Accept NIO 100						ON				
★	Reject NIO 100						OFF				
★	Accept NIO 500							ON			
★	Reject NIO 500							OFF			
★	Accept NIO 1000								ON		
★	Reject NIO 1000								OFF		
★	Accept USD 20									ON	
★	Reject USD 20									OFF	
★	Reserved										ON
★	Reserved										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

## L70-NIO3+USD1(ICT104U)

### DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Reserved		ON	OFF	
★	ICT104U Interface		OFF	ON	
★	Reserved				ON
	Reserved				OFF

## Currency Assign Data

Interface Bill value	ICT104U
BV1	NIO 100
BV2	NIO 500
BV3	NIO 1000
BV4	USD 20