

L70-TTD6

L70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT106U)

Supported bill TT\$ 1, 5, 10, 20, 50, 100 6 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / TT\$ 1	OFF	OFF	OFF							
	2 Pulse / TT\$ 1	OFF	OFF	ON							
	3 Pulse / TT\$ 1	OFF	ON	OFF							
	4 Pulse / TT\$ 1	OFF	ON	ON							
	5 Pulse / TT\$ 1	ON	OFF	OFF							
	10 Pulse / TT\$ 1	ON	OFF	ON							
	20 Pulse / TT\$ 1	ON	ON	OFF							
	100 Pulse / TT\$ 1	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept TT\$ 1				ON						
	Reject TT\$ 1				OFF						
★	Accept TT\$ 5				ON						
	Reject TT\$ 5				OFF						
★	Accept TT\$ 10 & 20				ON						
	Reject TT\$ 10 & 20				OFF						
★	Accept TT\$ 50				ON						
	Reject TT\$ 50				OFF						
★	Accept TT\$ 100				ON						
	Reject TT\$ 100				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit - Pulse Normal High	ON			
	Credit - Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	ICT Mode (ICT106U)		OFF		
★	Reserved			ON	
				OFF	
★	Reserved			ON	
				OFF	

Currency Assign Data

Interface Bill value	Pulse	ICT106U
BV1	1	1
BV2	5	5
BV3	10	10
BV4	20	20
BV5	100	100
BV6	50	50