

L70-USD6

L70/P5 DIP SWITCHES SETTING : 1(ICT104U/Pulse)

Supported bill US\$ 1, 5, 10, 20, 50, 100 6 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / US\$ 1	OFF	OFF	OFF							
	2 Pulse / US\$ 1	OFF	OFF	ON							
	3 Pulse / US\$ 1	OFF	ON	OFF							
	4 Pulse / US\$ 1	OFF	ON	ON							
	5 Pulse / US\$ 1	ON	OFF	OFF							
	10 Pulse / US\$ 1	ON	OFF	ON							
	20 Pulse / US\$ 1	ON	ON	OFF							
	100 Pulse / US\$ 1	ON	ON	ON							
	Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★	Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept US\$ 1 & 5						ON				
	Reject US\$ 1 & 5						OFF				
★	Accept US\$ 10							ON			
	Reject US\$ 10							OFF			
★	Accept US\$ 20								ON		
	Reject US\$ 20								OFF		
★	Accept US\$ 50									ON	
	Reject US\$ 50									OFF	
★	Accept US\$ 100										ON
	Reject US\$ 100										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit - Pulse Normal High	ON			
	Credit - Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	ICT104U Interface Mode		OFF		
	Reserved			ON	
★				OFF	
	Reserved				ON
★					OFF

Currency Assign Data

Interface Bill value	Pulse	ICT
BV1	US \$ 1	US \$ 1
BV2	US \$ 5	US \$ 5
BV3	US \$ 10	US \$ 10
BV4	US \$ 20	US \$ 20
BV5	US \$ 50	US \$ 50
BV6	US \$100	US \$100