

L70+/L70F-BDT6

L70+&L70F/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill BDT 10, 20, 50, 100, 500, 1000 6bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / BDT 10	OFF	OFF	OFF							
	2 Pulse / BDT 10	OFF	OFF	ON							
	3 Pulse / BDT 10	OFF	ON	OFF							
	4 Pulse / BDT 10	OFF	ON	ON							
	5 Pulse / BDT 10	ON	OFF	OFF							
	10 Pulse / BDT 10	ON	OFF	ON							
	20 Pulse / BDT 10	ON	ON	OFF							
	100 Pulse / BDT 10	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept BDT 10 & 20				ON						
★	Reject BDT 10 & 20				OFF						
★	Accept BDT 50				ON						
	Reject BDT 50				OFF						
★	Accept BDT 100				ON						
	Reject BDT 100				OFF						
★	Accept BDT 500				ON						
	Reject BDT 500				OFF						
★	Accept BDT 1000				ON						
	Reject BDT 1000				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit - Pulse Normal High	ON			
	Credit - Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	ICT104U Interface Mode		OFF		
	Reserved			ON	
★				OFF	
	Reserved				ON
★					OFF

Currency Assign Data

Interface Bill value	Pulse	ICT104U
BV1	BDT 10	BDT 10
BV2	BDT 20	BDT 20
BV3	BDT 50	BDT 50
BV4	BDT 100	BDT 100
BV5	BDT 500	BDT 500
BV6	BDT 1000	BDT 1000