

## L70+/L70F-LBP3

### L70+/L70F DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill LBP 1000, 5000, 10000 3bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / LBP 1000	OFF	OFF	OFF							
	2 Pulse / LBP 1000	OFF	OFF	ON							
	3 Pulse / LBP 1000	OFF	ON	OFF							
	4 Pulse / LBP 1000	OFF	ON	ON							
	5 Pulse / LBP 1000	ON	OFF	OFF							
	10 Pulse / LBP 1000	ON	OFF	ON							
	20 Pulse / LBP 1000	ON	ON	OFF							
	100 Pulse / LBP 1000	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept LBP 1000				ON						
	Reject LBP 1000				OFF						
★	Accept LBP 5000				ON						
	Reject LBP 5000				OFF						
★	Accept LBP 10000				ON						
	Reject LBP 10000				OFF						
★	Reserve				ON						
	Reserve				OFF						
★	Reserve				ON						
	Reserve				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

## L70+/L70F-LBP3(Pulse/ICT104U)

### DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Protocol		ON		
	ICT104U Protocol		OFF		
★	Reserved			ON	
				OFF	
★				ON	
				OFF	

★ Manufacture setting

### DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
★	Pulse Protocol		ON		
	ICT104U Protocol		OFF		
★	Reserved			ON	
				OFF	
★				ON	
				OFF	

★ Manufacture setting

### Currency Assign Data

Interface Bill value	Pulse	ICT104U
BV1	LBP 1000	LBP 1000
BV2	LBP 5000	LBP 5000
BV3	LBP 10000	LBP 10000