

## V7E/LX7-RUB6

### V7E/LX7 Option Switch Settings: 1(Pulse/ICT104U/MDB)

Supported bill Ruble 10, 50, 100, 500, 1000, 5000 6bills.

V7E/LX7 dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★	Reject Ruble 10 (Note.4)	ON											
★	Accept Ruble 10 (Note.4)	OFF											
★	Reject Ruble 50		ON										
★	Accept Ruble 50		OFF										
★	Reject Ruble 100			ON									
★	Accept Ruble 100			OFF									
★	Reject Ruble 500				ON								
★	Accept Ruble 500				OFF								
★	Reject Ruble 1000					ON							
★	Accept Ruble 1000					OFF							
★	Reject Ruble 5000						ON						
★	Accept Ruble 5000						OFF						
	<b>Pulse Mode</b>	<b>Other Mode</b>											
★	Harness Disable	BA stops working when fishing					ON						
★	Harness Enable	Normal					OFF						
★	Inhibit Active High						ON						
★	Inhibit Active Low						OFF						
★	1 pulse / Ruble 10 & 50						OFF	OFF					
★	2 pulses / Ruble 10 & 50						ON	OFF					
★	5 pulses / Ruble 10 & 50						OFF	ON					
★	20 pulses / Ruble 10 & 50						ON	ON					
★	Pulse Speed	50ms LO / 50ms HI								OFF	OFF		
		60ms LO / 300ms HI								ON	OFF		
		30ms LO / 50ms HI								OFF	ON		
		150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

Note : 1.Default setting

2. Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

3. Remove the front cover and the dip-switch in on the CPU board.

4. Pulse Mode:

When Dip 1 is OFF, One Pulse per RUB 10.

When Dip 1 is ON, One Pulse per RUB 50.

MDB Mode:

When Dip 1 is OFF, Reject RUB 5000.

When Dip 1 is ON, Accept RUB 5000.

## V7E/LX7-RUB6(Pulse/ICT104U/MDB)

### DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
	MDB Interface		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

### Currency Assign Data

Interface	ICT104U	Pulse		MDB	
		When Dip 1 is ON	When Dip 1 is OFF	When Dip 1 is ON	When Dip 1 is OFF
BV1	Ruble 10		Ruble 10	Ruble 50	Ruble 10
BV2	Ruble 50	Ruble 50	Ruble 50	Ruble 100	Ruble 50
BV3	Ruble 100	Ruble 100	Ruble 100	Ruble 500	Ruble 100
BV4	Ruble 500	Ruble 500	Ruble 500	Ruble 1000	Ruble 500
BV5	Ruble 1000	Ruble 1000	Ruble 1000	Ruble 5000	Ruble 1000
BV6	Ruble 5000	Ruble 5000	Ruble 5000		

### DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	Pulse Mode		ON	OFF	
★	ICT104U Interface		OFF	ON	
	MDB Interface		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

### DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Interface		OFF	ON	
	MDB Interface		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting