



AED5

P70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT)

Supported bill Dh 5, 10, 20, 50, 100 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10	
★	1 Pulse / Dh 5	OFF	OFF	OFF								
	2 Pulse / Dh 5	OFF	OFF	ON								
	3 Pulse / Dh 5	OFF	ON	OFF								
	4 Pulse / Dh 5	OFF	ON	ON								
	5 Pulse / Dh 5	ON	OFF	OFF								
	10 Pulse / Dh 5	ON	OFF	ON								
	20 Pulse / Dh 5	ON	ON	OFF								
	100 Pulse / Dh 5	ON	ON	ON								
	Fast output Pulse Lo=50ms Hi=100ms											ON
★	Slow output Pulse Lo=50ms Hi=300ms											OFF
	Inhibit level Active Low					ON						
★	Inhibit level Active High					OFF						
★	Accept Dh 5						ON					
	Reject Dh 5						OFF					
★	Accept Dh 10							ON				
	Reject Dh 10							OFF				
★	Accept Dh 20								ON			
	Reject Dh 20								OFF			
★	Accept Dh 50									ON		
	Reject Dh 50									OFF		
★	Accept Dh 100										ON	
	Reject Dh 100										OFF	

★ Manufacture setting

Note: (1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4	
★	Pulse Normal High	ON				
	Pulse Normal Low	OFF				
★	Pulse Protocol					ON
	ICT Protocol					OFF
	Harness Disable			ON		
★	Harness Enable			OFF		
	Ignore Sensor Problem(Note 1)				ON	
★	Acknowledge Sensor Problem (Note 2)				OFF	

★ Manufacture setting

Note : (1) Sensor 6 problem occurred ==>> BA will be still in working order.

(The face LED will be flashing in short green about 2 seconds everytime you restart BA.)

(2) BA will stop to work when it acknowledges Sensor 6 problem occurred.

(The face LED will be flashing in red.)

