

## P70-ARS7

### P70/P2/P5 DIP SWITCHES SETTING : 1(Pulse/M.D.B)

Supported bill Pesos 5, 10, 20, 50, 100, 200, 500 7bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / ARS 1	OFF	OFF	OFF							
2 Pulse / ARS 1	OFF	OFF	ON							
3 Pulse / ARS 1	OFF	ON	OFF							
4 Pulse / ARS 1	OFF	ON	ON							
5 Pulse / ARS 1	ON	OFF	OFF							
10 Pulse / ARS 1	ON	OFF	ON							
20 Pulse / ARS 1	ON	ON	OFF							
100 Pulse / ARS 1	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi= 100ms				ON						
★ Slow output Pulse Lo= 50ms Hi= 300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept Pesos 5						ON				
Reject Pesos 5						OFF				
★ Accept Pesos 10							ON			
Reject Pesos 10							OFF			
★ Accept Pesos 20 & 50								ON		
Reject Pesos 20 & 50								OFF		
★ Accept Pesos 100 & 200									ON	
Reject Pesos 100 & 200									OFF	
★ Accept Pesos 500										ON
Reject Pesos 500										OFF

★ Manufacture setting

Note: (1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

## P70-ARS7/P2/P5(Pulse/M.D.B)

### DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON		
M.D.B Interface		OFF		
Harness Disable			ON	
★ Harness Enable			OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

### DIP SWITCHES SETTING : 2(M.D.B)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON		
★ M.D.B Interface		OFF		
★ Reserved			ON	
Reserved			OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

### Currency Assign Data

Interface Bill value	Pulse	MDB
BV1	ARS 5	ARS 5
BV2	ARS 10	ARS 10
BV3	ARS 20	ARS 20
BV4	ARS 50	ARS 50
BV5	ARS 100	ARS 100
BV6	ARS 200	ARS 200
BV7	ARS 500	ARS 500