

**Supported bill Ch\$ 1000, 2000, 5000, 10000 4bills.**

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / Ch\$ 1000	OFF	OFF	OFF							
2 Pulse / Ch\$ 1000	OFF	OFF	ON							
3 Pulse / Ch\$ 1000	OFF	ON	OFF							
4 Pulse / Ch\$ 1000	OFF	ON	ON							
5 Pulse / Ch\$ 1000	ON	OFF	OFF							
10 Pulse / Ch\$ 1000	ON	OFF	ON							
20 Pulse / Ch\$ 1000	ON	ON	OFF							
100 Pulse / Ch\$ 1000	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept Ch\$ 1000						ON				
Reject Ch\$ 1000						OFF				
★ Accept Ch\$ 2000							ON			
Reject Ch\$ 2000							OFF			
★ Accept Ch\$ 05000 & 010000								ON		
Reject Ch\$ 05000 & 010000								OFF		
★ Accept Ch\$ N5000 (2009)									ON	
Reject Ch\$ N5000 (2009)									OFF	
★ Accept Ch\$ N10000 (2010)										ON
Reject Ch\$ N10000 (2010)										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

## DIP SWITCHES SETTING : 2

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal High	ON			
Credit-Pulse Normal Low	OFF			
★ Pulse Protocol		ON		
ICT Protocol		OFF		
Harness Disable			ON	
★ Harness Enable			OFF	
Manufacture Default				ON
★ System Default				OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 & 3 are only used for pulse protocol.

## Currency Assign Data

Interface Bill value	ICT	Pulse
BV1	1000	1000
BV2	2000	2000
BV3	O 5000	O 5000
BV4	N 5000	N 5000
BV5	O 10000	O 10000
BV6	N 10000	N 10000