



DOP7

P70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT)

Supported bill RD\$ 10, 20, 50, 100, 200, 500, 1000 7bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / RD\$ 10	OFF	OFF	OFF							
	2 Pulse / RD\$ 10	OFF	OFF	ON							
	3 Pulse / RD\$ 10	OFF	ON	OFF							
	4 Pulse / RD\$ 10	OFF	ON	ON							
	5 Pulse / RD\$ 10	ON	OFF	OFF							
	10 Pulse / RD\$ 10	ON	OFF	ON							
	20 Pulse / RD\$ 10	ON	ON	OFF							
	100 Pulse / RD\$ 10	ON	ON	ON							
	Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★	Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept RD\$ 10 & 20						ON				
	Reject RD\$ 10 & 20						OFF				
★	Accept RD\$ 50 & 100							ON			
	Reject RD\$ 50 & 100							OFF			
★	Accept RD\$ 200								ON		
	Reject RD\$ 200								OFF		
★	Accept RD\$ 500									ON	
	Reject RD\$ 500									OFF	
★	Accept RD\$ 1000										ON
	Reject RD\$ 1000										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Protocol		ON		
	ICT Protocol		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
	Manufacture Default				ON
★	System Default				OFF

★ Manufacture setting

