

P70-EUR2

P70/P5 DIP SWITCHES SETTING : 1(Pulse/MDB)

Supported bill € 5, 10

2bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / € 5	OFF	OFF	OFF							
	2 Pulse / € 5	OFF	OFF	ON							
	3 Pulse / € 5	OFF	ON	OFF							
	4 Pulse / € 5	OFF	ON	ON							
	5 Pulse / € 5	ON	OFF	OFF							
	10 Pulse / € 5	ON	OFF	ON							
	20 Pulse / € 5	ON	ON	OFF							
	100 Pulse / € 5	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept € 5						ON				
	Reject € 5						OFF				
★	Accept € 10							ON			
	Reject € 10							OFF			
★	Accept Normal								ON		
	Reject € 5(2002) & 10(2002)								OFF		
★	Reserved									ON	
	Reserved									OFF	
★	Reserved										ON
	Reserved										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

P70-EUR2/P5(Pulse/MDB)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	MDB Interface		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 & 3 are only used for pulse protocol.

DIP SWITCHES SETTING : 3(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON		
★	MDB Interface		OFF		
	Reserved			ON	
★	Reserved			OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB
BV1	5	5
BV2	10	10