

EUR2

P70/P5 DIP SWITCHES SETTING : 1(Pulse/Parallel A3)

Supported bill € 5, 10

2bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / € 5	OFF	OFF	OFF							
	2 Pulses / € 5	OFF	OFF	ON							
	3 Pulses / € 5	OFF	ON	OFF							
	4 Pulses / € 5	OFF	ON	ON							
	5 Pulses / € 5	ON	OFF	OFF							
	10 Pulses / € 5	ON	OFF	ON							
	20 Pulses / € 5	ON	ON	OFF							
	100 Pulses / € 5	ON	ON	ON							
	Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★	Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept € 5					ON					
	Reject € 5					OFF					
★	Accept € 10						ON				
	Reject € 10						OFF				
	Reserved							ON			
★	Reserved							OFF			
	Reserved								ON		
★	Reserved								OFF		
	Reserved									ON	
★	Reserved									OFF	

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

P70-EUR2/P5(Pulse/Parallel A3)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal HIGH	ON			
	Credit-Pulse Normal LOW	OFF			
★	Pulse Mode		ON		
	Parallel A3 Mode		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
	Manufacture Default				ON
★	System Default				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(Parallel A3)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	Parallel A3 Mode		OFF		
	Reserved			ON	
★	Reserved			OFF	
	Manufacture Default				ON
★	System Default				OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 & 3 are only used for pulse protocol.

Currency Assign Data

Interface Bill value	Parallel A3	Pulse
BV1	€ 5	€ 5
BV2	€ 10	€ 10