



SGD3

P70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT)

Supported bill S\$ 2, 5, 10

3bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / S\$ 1	OFF	OFF	OFF							
2 Pulse / S\$ 1	OFF	OFF	ON							
3 Pulse / S\$ 1	OFF	ON	OFF							
4 Pulse / S\$ 1	OFF	ON	ON							
5 Pulse / S\$ 1	ON	OFF	OFF							
10 Pulse / S\$ 1	ON	OFF	ON							
20 Pulse / S\$ 1	ON	ON	OFF							
100 Pulse / S\$ 1	ON	ON	ON							
Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept S\$ 2						ON				
Reject S\$ 2						OFF				
★ Accept S\$ 5							ON			
Reject S\$ 5							OFF			
★ Accept S\$ 10								ON		
Reject S\$ 10								OFF		
★ Reserved									ON	
									OFF	
										ON
★										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.
 (2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Protocol		ON		
ICT Protocol		OFF		
Harness Disable			ON	
★ Harness Enable			OFF	
Manufacture Default				ON
★ System Default				OFF

★ Manufacture setting