

P70-TWD4

P70/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill TWD 100, 200, 500, 1000

4bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10							
★ 1 Pulse / TWD 100	OFF	OFF	OFF														
2 Pulse / TWD 100	OFF	OFF	ON														
3 Pulse / TWD 100	OFF	ON	OFF														
4 Pulse / TWD 100	OFF	ON	ON														
5 Pulse / TWD 100	ON	OFF	OFF														
10 Pulse / TWD 100	ON	OFF	ON														
20 Pulse / TWD 100	ON	ON	OFF														
100 Pulse / TWD 100	ON	ON	ON														
Fast output Pulse Lo=100ms Hi=100ms				ON													
★ Slow output Pulse Lo=100ms Hi=300ms				OFF													
Inhibit level Active Low				ON													
★ Inhibit level Active High				OFF													
★ Accept TWD 100											ON						
Reject TWD 100											OFF						
★ Accept TWD 200											ON						
Reject TWD 200											OFF						
★ Accept TWD 500											ON						
Reject TWD 500											OFF						
★ Accept TWD 1000									ON								
Reject TWD 1000									OFF								
Reserved										ON							
★ Reserved										OFF							

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Protocol		ON		
ICT104U Protocol		OFF		
Harness Disable			ON	
★ Harness Enable			OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT104U
BV1	TWD 100	TWD 100
BV2	TWD 200	TWD 200
BV3	TWD 500	TWD 500
BV4	TWD 1000	TWD 1000