

P77-CZK6

P77/P5 DIP SWITCHES SETTING : 1(Pulse/RS232 A1)

Supported bill CZK 100, 200, 500, 1000, 2000, 5000 6bills.
 With stacker CZK 100, 200, 500, 1000, 2000, 5bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / CZK 50	OFF	OFF	OFF							
2 Pulses / CZK 50	OFF	OFF	ON							
3 Pulses / CZK 50	OFF	ON	OFF							
4 Pulses / CZK 50	OFF	ON	ON							
5 Pulses / CZK 50	ON	OFF	OFF							
10 Pulses / CZK 50	ON	OFF	ON							
20 Pulses / CZK 50	ON	ON	OFF							
100 Pulses / CZK 50	ON	ON	ON							
Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept CZK 100						ON				
Reject CZK 100						OFF				
★ Accept CZK 200 & 500							ON			
Reject CZK 200 & 500							OFF			
★ Accept CZK 1000								ON		
Reject CZK 1000								OFF		
★ Accept CZK 2000									ON	
Reject CZK 2000									OFF	
★ Accept CZK 5000										ON
Reject CZK 5000										OFF

★ Manufacture setting

Note: (1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2 Currency Assign Data

FUNCTION		SW1	SW2	SW3	SW4	Interface	RS232 A1	Pulse
RS232 A1 Protocol	Pulse Protocol					Bill value		
★ Reserved	Credit-Pulse Normal High	ON				BV1		
Reserved	Credit-Pulse Normal Low	OFF				BV2	CZK 100	CZK 100
Pulse Protocol	★ Pulse Protocol		ON			BV3	CZK 200	CZK 200
★ RS232 A1 Protocol	RS232 A1 Protocol		OFF			BV4	CZK 500	CZK 500
Reserved	Harness Disable			ON		BV5	CZK 1000	CZK 1000
★ Reserved	Harness Enable			OFF		BV6	CZK 2000	CZK 2000
Reserved	Reserved				ON	BV7	CZK 5000	CZK 5000
★ Reserved	Reserved				OFF			

★ Manufacture setting

Note : (1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 & 3 are only used for pulse protocol.