



AMD4

P77/P5 DIP SWITCHES SETTING : 1(Pulse/ICT)

Supported bill DRAMS 1000, 5000, 10000, 20000 4 bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / DRAMS 1000	OFF	OFF	OFF							
2 Pulse / DRAMS 1000	OFF	OFF	ON							
3 Pulse / DRAMS 1000	OFF	ON	OFF							
4 Pulse / DRAMS 1000	OFF	ON	ON							
5 Pulse / DRAMS 1000	ON	OFF	OFF							
10 Pulse / DRAMS 1000	ON	OFF	ON							
20 Pulse / DRAMS 1000	ON	ON	OFF							
100 Pulse / DRAMS 1000	ON	ON	ON							
Fast output Pulse <small>Lo= 50ms Hi=100ms</small>				ON						
★ Slow output Pulse <small>Lo= 50ms Hi=300ms</small>				OFF						
Inhibit level Active Low				ON						
Inhibit level Active High				OFF						
★ Accept DRAMS 1000				ON						
Reject DRAMS 1000				OFF						
★ Accept DRAMS 5000				ON						
Reject DRAMS 5000				OFF						
★ Accept DRAMS 10000				ON						
Reject DRAMS 10000				OFF						
★ Accept DRAMS 20000				ON						
Reject DRAMS 20000				OFF						
Reserved				ON						
★ Reserved				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Protocol		ON		
ICT Protocol		OFF		
Harness Disable			ON	
★ Harness Enable			OFF	
Manufacture Default				ON
★ System Default				OFF

★ Manufacture setting

