

P77-MKD4

P77/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill MKD 10, 50, 100, 200 4 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / MKD 10	OFF	OFF	OFF							
	2 Pulse / MKD 10	OFF	OFF	ON							
	3 Pulse / MKD 10	OFF	ON	OFF							
	4 Pulse / MKD 10	OFF	ON	ON							
	5 Pulse / MKD 10	ON	OFF	OFF							
	10 Pulse / MKD 10	ON	OFF	ON							
	20 Pulse / MKD 10	ON	ON	OFF							
	100 Pulse / MKD 10	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept MKD 10				ON						
	Reject MKD 10				OFF						
★	Accept MKD 50				ON						
	Reject MKD 50				OFF						
★	Accept MKD 100				ON						
	Reject MKD 100				OFF						
★	Accept MKD 200				ON						
	Reject MKD 200				OFF						
★	Reserved				ON						
	Reserved				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

Currency Assign Data

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Protocol		ON		
	ICT104U Protocol		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
	Reserved				ON
★	Reserved				OFF

Interface Bill value	Pulse	ICT104U
BV1	MKD 10	MKD 10
BV2	MKD 50	MKD 50
BV3	MKD 100	MKD 100
BV4	MKD 200	MKD 200

★ Manufacture setting

Appendix