

P77-PLN5

P77/P2/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill zloty 10, 20, 50, 100, 200 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / zloty 10	OFF	OFF	OFF							
	2 Pulse / zloty 10	OFF	OFF	ON							
	3 Pulse / zloty 10	OFF	ON	OFF							
	4 Pulse / zloty 10	OFF	ON	ON							
	5 Pulse / zloty 10	ON	OFF	OFF							
	10 Pulse / zloty 10	ON	OFF	ON							
	20 Pulse / zloty 10	ON	ON	OFF							
	100 Pulse / zloty 10	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept zloty 10				ON						
	Reject zloty 10				OFF						
★	Accept zloty 20				ON						
	Reject zloty 20				OFF						
★	Accept zloty 50				ON						
	Reject zloty 50				OFF						
★	Accept zloty 100				ON						
	Reject zloty 100				OFF						
★	Accept zloty 200				ON						
	Reject zloty 200				OFF						

★ Manufacture setting

Note: (1)Please reset the bill acceptor after set the dip switch.
(2)Dip switches 1 to 5 are only used for pulse protocol.

P77-PLN5/P2/P5(Pulse/ICT104U)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	ICT Interface		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
	Reserved	OFF			
	Pulse Mode		ON		
★	ICT Interface		OFF		
	Reserved			ON	
★	Reserved			OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	Pulse
BV1	zloty 10	zloty 10
BV2	zloty 20	zloty 20
BV3	zloty 50	zloty 50
BV4	zloty 100	zloty 100
BV5	zloty 200	zloty 200