

## P77-RON4

### P77/P2/P5 DIP SWITCHES SETTING : 1(Pulse/M.D.B)

Supported bill Lei 1, 5, 10, 50 4bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / Lei 1	OFF	OFF	OFF							
2 Pulse / Lei 1	OFF	OFF	ON							
3 Pulse / Lei 1	OFF	ON	OFF							
4 Pulse / Lei 1	OFF	ON	ON							
5 Pulse / Lei 1	ON	OFF	OFF							
10 Pulse / Lei 1	ON	OFF	ON							
20 Pulse / Lei 1	ON	ON	OFF							
100 Pulse / Lei 1	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept Lei 1						ON				
Reject Lei 1						OFF				
★ Accept Lei 5							ON			
Reject Lei 5							OFF			
★ Accept Lei 10								ON		
Reject Lei 10								OFF		
★ Accept Lei 50									ON	
Reject Lei 50									OFF	
Reserved										ON
★ Reserved										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

## P77-RON4/P2/P5(Pulse/M.D.B)

### DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON		
M.D.B Interface		OFF		
Harness Disable			ON	
★ Harness Enable			OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting.

### DIP SWITCHES SETTING : 3(M.D.B)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
Pulse Mode		ON		
★ M.D.B Interface		OFF		
Reserved			ON	
★ Reserved			OFF	
Reserved				ON
★ Reserved				OFF

★ Manufacture setting.

### Currency Assign Data

Interface Bill value	Pulse	MDB
BV1	Lei 1	Lei 1
BV2	Lei 5	Lei 5
BV3	Lei 10	Lei 10
BV4	Lei 50	Lei 50