

P77-THB5

P77/P5 DIP SWITCHES SETTING : 1(Pulse/ICT002)

Supported bill THB 20, 50, 100, 500, 1000 5bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / THB 10	OFF	OFF	OFF							
2 Pulse / THB 10	OFF	OFF	ON							
3 Pulse / THB 10	OFF	ON	OFF							
4 Pulse / THB 10	OFF	ON	ON							
5 Pulse / THB 10	ON	OFF	OFF							
10 Pulse / THB 10	ON	OFF	ON							
20 Pulse / THB 10	ON	ON	OFF							
100 Pulse / THB 10	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept THB 20						ON				
Reject THB 20						OFF				
★ Accept THB 50							ON			
Reject THB 50							OFF			
★ Accept THB 100								ON		
Reject THB 100								OFF		
★ Accept THB 500									ON	
Reject THB 500									OFF	
★ Accept THB 1000										ON
Reject THB 1000										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

FUNCTION	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal High	ON			
★ Credit-Pulse Normal Low	OFF			
★ Pulse Protocol		ON		
ICT002 Protocol		OFF		
Harness Disable			ON	
★ Harness Enable			OFF	
★ Reserved				ON
Reserved				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT002	Pulse
BV1	20	20
BV2	50	50
BV3	100	100
BV4	500	500
BV5	1000	1000