

## P77-TRY6

### P77/P5 DIP SWITCHES SETTING : 1(Pulse/RS232 A0)

Supported bill £ 5, 10, 20, 50, 100, 200

6 bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / £ 5	OFF	OFF	OFF							
2 Pulse / £ 5	OFF	OFF	ON							
3 Pulse / £ 5	OFF	ON	OFF							
4 Pulse / £ 5	OFF	ON	ON							
5 Pulse / £ 5	ON	OFF	OFF							
10 Pulse / £ 5	ON	OFF	ON							
20 Pulse / £ 5	ON	ON	OFF							
100 Pulse / £ 5	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low					ON					
★ Inhibit level Active High					OFF					
★ Accept £ 5 & 10						ON				
Reject £ 5 & 10						OFF				
★ Accept £ 20							ON			
Reject £ 20							OFF			
★ Accept £ 50								ON		
Reject £ 50								OFF		
★ Accept £ 100									ON	
Reject £ 100									OFF	
★ Accept £ 200										ON
Reject £ 200										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

## P77-TRY6/P5(Pulse/RS232 A0)

### DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON		
RS232 A0 Mode		OFF		
Harness Disable			ON	
★ Harness Enable			OFF	
Manufacture Default				ON
★ System Default				OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 & 3 are only used for pulse protocol.

### Currency Assign Data

Interface Bill value	Pulse	RS232 A0
BV1	5	5
BV2	10	10
BV3	20	20
BV4	50	50
BV5	100	100
BV6	200	200

### DIP SWITCHES SETTING : 2(RS232 A0)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON		
★ RS232 A0 Mode		OFF		
Reserved			ON	
★ Reserved			OFF	
Manufacture Default				ON
★ System Default				OFF

★ Manufacture setting

Note:

ESCROW DATA	
Code	Denomination
61h	Reserved
62h	Reserved
63h	£ 5
64h	£ 10
65h	£ 20
66h	£ 50
67h	£ 100
68h	£ 200

CURRENCY ASSIGN DATA			
Code	Country	Denomination	Exp.
61h	00	00	00
62h	00	00	00
63h	7B	05	00
64h	7B	0A	00
65h	7B	14	00
66h	7B	32	00
67h	7B	64	00
68h	7B	C8	00