

P77-UYU7

P77/P5 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill UYU 20, 50, 100, 200, 500, 1000, 2000 7bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / UYU 10	OFF	OFF	OFF							
	2 Pulse / UYU 10	OFF	OFF	ON							
	3 Pulse / UYU 10	OFF	ON	OFF							
	4 Pulse / UYU 10	OFF	ON	ON							
	5 Pulse / UYU 10	ON	OFF	OFF							
	10 Pulse / UYU 10	ON	OFF	ON							
	20 Pulse / UYU 10	ON	ON	OFF							
	100 Pulse / UYU 10	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept UYU 20 & 50				ON						
	Reject UYU 20 & 50				OFF						
★	Accept UYU 100 & 200				ON						
	Reject UYU 100 & 200				OFF						
★	Accept UYU 500				ON						
	Reject UYU 500				OFF						
★	Accept UYU 1000				ON						
	Reject UYU 1000				OFF						
★	Accept UYU 2000				ON						
	Reject UYU 2000				OFF						

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Protocol		ON		
	ICT104U Protocol		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	Pulse
BV1	UYU 20	UYU 20
BV2	UYU 50	UYU 50
BV3	UYU 100	UYU 100
BV4	UYU 200	UYU 200
BV5	UYU 500	UYU 500
BV6	UYU 1000	UYU 1000
BV7	UYU 2000	UYU 2000