

P85-ROL7

P85/P5 DIP SWITCHES SETTING : 1(Pulse/Special RS232 A0)

Supported bill Lei 1, 5, 10, 50, 100, 200, 500
7 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10	
★	1 Pulse / Lei 1	OFF	OFF	OFF								
	2 Pulses / Lei 1	OFF	OFF	ON								
	3 Pulses / Lei 1	OFF	ON	OFF								
	4 Pulses / Lei 1	OFF	ON	ON								
	5 Pulses / Lei 1	ON	OFF	OFF								
	10 Pulses / Lei 1	ON	OFF	ON								
	20 Pulses / Lei 1	ON	ON	OFF								
	100 Pulses / Lei 1	ON	ON	ON								
★	Fast output Pulse Lo= 75ms Hi= 75ms				ON							
	Slow output Pulse Lo=100ms Hi=150ms				OFF							
★	Inhibit level Active Low				ON							
	Inhibit level Active High				OFF							
★	Accept Lei 1					ON						
	Reject Lei 1					OFF						
★	Accept Lei 5					ON						
	Reject Lei 5					OFF						
★	Accept Lei 10								ON			
	Reject Lei 10								OFF			
★	Accept Lei 50 & 100									ON		
	Reject Lei 50 & 100									OFF		
★	Accept Lei 200 & 500										ON	
	Reject Lei 200 & 500										OFF	

★ Manufacture setting

Note: (1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Protocol		ON		
	RS232 A0 Protocol		OFF		
	Harness Disable			ON	
★	Harness Enable			OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

P85-ROL7/P5(Pulse/Special RS232 A0)

DIP SWITCHES SETTING : 2(Special RS232 A0)

	FUNCTION	SW1	SW2	SW3	SW4
★	Not used	ON			
	Not used	OFF			
	Pulse Protocol		ON		
★	RS232 A0 Protocol		OFF		
	Special customer requirements 2			ON	
★	Special customer requirements 1			OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

★ RS232 A0 INFORMATION

1.Special customer requirements 1

BillType Data	
Code	Denomination
1	Lei 1
2	Reserved
3	Lei 5
4	Lei 10
5	Reserved
6	Lei 50
7	Lei 100
8	Lei 200
9	Lei 500

2.Special customer requirements 2

BillType Data	
Code	Denomination
1	Lei 1
2	Reserved
3	Reserved
4	Lei 5
5	Lei 10
6	Lei 50
7	Lei 100
8	Lei 200
9	Lei 500

Currency Assign Data

Interface Bill value	RS232 A0	Pulse
BV1	Lei 1	Lei 1
BV2	Lei 5	Lei 5
BV3	Lei 10	Lei 10
BV4	Lei 50	Lei 50
BV5	Lei 100	Lei 100
BV6	Lei 200	Lei 200
BV7	Lei 500	Lei 500