

SCA1-CHF6

SCA1 DIP SWITCHES SETTING : 1(Pulse/Parallel/RS232)

Supported coin CHF 0.1, 0.2, 0.5, 1, 2, 5 6 coins.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6
	Pulse (25ms)	OFF	OFF				
★	Pulse (45ms)	ON	OFF				
	Pulse (60ms)	OFF	ON				
	Pulse (100ms)	ON	ON				
★	Accept CHF 0.1, 0.2, 0.5, 1			ON			
	Reject CHF 0.1, 0.2, 0.5, 1			OFF			
★	Accept CHF 2				ON		
	Reject CHF 2				OFF		
★	Accept CHF 5					ON	
	Reject CHF 5					OFF	
★	Normal Open						ON
	Normal Close						OFF

★ Manufacture setting

Currency Assign Data

Channel Currency	Paralle	Coin : Credit Normal Pulse
Channel 1 : \$0.1	1	1 : 1
Channel 2 : \$0.2	2	1 : 2
Channel 3 : \$0.5	3	1 : 5
Channel 4 : \$1	4	1 : 10
Channel 5 : \$2	5	1 : 20
Channel 6 : \$5	6	1 : 50