

## TAO-V+MXN9

### TAO-V Option Switch Settings: 1(Pulse/MDB)

Supported bill MXN 20, 50, 100, 200, 500  
USD 1, 5, 10, 20 9bills.

TAO-V dip-switch settings and functions:

|   | FUNCTION                                    | SW1                           | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW1 | SW2 | SW3 | SW4 |
|---|---------------------------------------------|-------------------------------|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|-----|
| ★ | Reject MXN 20 & USD 1                       | ON                            |     |     |     |     |     |     |     |     |     |     |     |
|   | Accept MXN 20 & USD 1                       | OFF                           |     |     |     |     |     |     |     |     |     |     |     |
| ★ | Reject MXN 50 & USD 5                       |                               | ON  |     |     |     |     |     |     |     |     |     |     |
| ★ | Accept MXN 50 & USD 5                       |                               | OFF |     |     |     |     |     |     |     |     |     |     |
| ★ | Reject MXN 100 & USD 10                     |                               |     | ON  |     |     |     |     |     |     |     |     |     |
| ★ | Accept MXN 100 & USD 10                     |                               |     | OFF |     |     |     |     |     |     |     |     |     |
| ★ | Reject MXN 200 & MXN 500 & USD 20           |                               |     |     | ON  |     |     |     |     |     |     |     |     |
| ★ | Accept MXN 200 & MXN 500 & USD 20           |                               |     |     | OFF |     |     |     |     |     |     |     |     |
| ★ | Accept Mexico Pesos and US Dollars (Note 3) |                               |     |     |     | ON  |     |     |     |     |     |     |     |
| ★ | Accept Mexico Pesos Only (Note 3)           |                               |     |     |     | OFF |     |     |     |     |     |     |     |
| ★ | Reserved                                    |                               |     |     |     | ON  |     |     |     |     |     |     |     |
| ★ | Reserved                                    |                               |     |     |     | OFF |     |     |     |     |     |     |     |
|   | <b>Pulse Mode</b>                           | <b>Other Mode</b>             |     |     |     |     |     |     |     |     |     |     |     |
|   | Harness Disable                             | BA stops working when fishing |     |     |     |     |     | ON  |     |     |     |     |     |
| ★ | Harness Enable                              | Normal                        |     |     |     |     |     | OFF |     |     |     |     |     |
| ★ | Inhibit Active High                         |                               |     |     |     |     |     | ON  |     |     |     |     |     |
| ★ | Inhibit Active Low                          |                               |     |     |     |     |     | OFF |     |     |     |     |     |
| ★ | 1 pulse / MXN 10 & USD 1                    |                               |     |     |     |     |     | OFF | OFF |     |     |     |     |
|   | 2 pulses / MXN 10 & USD 1                   |                               |     |     |     |     |     | ON  | OFF |     |     |     |     |
|   | 5 pulses / MXN 10 & USD 1                   |                               |     |     |     |     |     | OFF | ON  |     |     |     |     |
|   | 10 pulses / MXN 10 & USD 1                  |                               |     |     |     |     |     | ON  | ON  |     |     |     |     |
| ★ | Interface Timing Conversion                 | 50ms LO / 50ms HI             |     |     |     |     |     |     |     | OFF | OFF |     |     |
|   |                                             | 60ms LO / 300ms HI            |     |     |     |     |     |     |     | ON  | OFF |     |     |
|   |                                             | 30ms LO / 50ms HI             |     |     |     |     |     |     |     | OFF | ON  |     |     |
|   |                                             | 150ms LO / 150ms HI           |     |     |     |     |     |     |     | ON  | ON  |     |     |

★ Manufacture setting

Note : (1) Default setting

(2) Use 2nd dip switch of the internal dip-switch to change different interface protocol.

(3) For Accepting US Dollars, make sure you have dip 5 set to ON position.

(\* Exchange Rate on USD to MXN is 1:15 for MDB Mode)

## TAO-V+MXN9(Pulse/MDB)

### Interface Settings: 2(Pulse)

|   | INTERFACE                | SW1 | SW2 | SW3 | SW4 |
|---|--------------------------|-----|-----|-----|-----|
| ★ | Credit-Pulse Normal HIGH | ON  |     |     |     |
|   | Credit-Pulse Normal LOW  | OFF |     |     |     |
| ★ | Pulse Mode               |     | ON  |     |     |
|   | MDB Interface            |     | OFF |     |     |
| ★ | Reserved                 |     |     | ON  |     |
|   |                          |     |     | OFF |     |
| ★ | Reserved                 |     |     |     | ON  |
|   |                          |     |     |     | OFF |

★ Manufacture setting

### Interface Settings: 2(MDB)

|   | INTERFACE                                                     | SW1 | SW2 | SW3 | SW4 |
|---|---------------------------------------------------------------|-----|-----|-----|-----|
| ★ | Scaling Factor (SF) = 100<br>Decimal Point Position (DPP) = 2 | ON  |     |     |     |
|   | Scaling Factor (SF) = 100<br>Decimal Point Position (DPP) = 2 | OFF |     |     |     |
| ★ | Pulse Mode                                                    |     | ON  |     |     |
| ★ | MDB Interface                                                 |     | OFF |     |     |
| ★ | Reserved                                                      |     |     | ON  |     |
|   |                                                               |     |     | OFF |     |
| ★ | Reserved                                                      |     |     |     | ON  |
|   |                                                               |     |     |     | OFF |

★ Manufacture setting

### Currency Assign Data

| Interface<br>Bill value | Pulse   | MDB     |
|-------------------------|---------|---------|
| BV1                     | USD 1   | USD 1   |
| BV2                     | MXN 20  | MXN 20  |
| BV3                     | MXN 50  | MXN 50  |
| BV4                     | MXN 100 | MXN 100 |
| BV5                     | MXN 200 | MXN 200 |
| BV6                     | MXN 500 | MXN 500 |
| BV7                     | USD 5   | USD 5   |
| BV8                     | USD 10  | USD 10  |
| BV9                     | USD 20  | USD 20  |