

V77E-RUB7

V77E Option Switch Settings : 1(Pulse/RS232 A0/ccNet/ICT104U)

Supported bill RUB 50, 100, 200, 500, 1000, 2000, 5000 7bills.

V77E dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject RUB 50 & 100	ON											
★ Accept RUB 50 & 100	OFF											
★ Reject RUB 200		ON										
★ Accept RUB 200		OFF										
★ Reject RUB 500 & 1000			ON									
★ Accept RUB 500 & 1000			OFF									
★ Reject RUB 2000				ON								
★ Accept RUB 2000				OFF								
★ Reject RUB 5000					ON							
★ Accept RUB 5000					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / RUB 50									OFF	OFF		
★ 5 pulses / RUB 50									ON	OFF		
★ 10 pulses / RUB 50									OFF	ON		
★ 20 pulses / RUB 50									ON	ON		
★ Pulse Speed	50ms LO / 50ms HI										OFF	OFF
	60ms LO / 300ms HI										ON	OFF
	30ms LO / 50ms HI										OFF	ON
	150ms LO / 150ms HI										ON	ON

★ Manufacture setting

◆ Factory configuration has all switches in the OFF position.

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

(3) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

V77E-RUB7(Pulse/RS232 A0/ccNet/ICT104U)

Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Interface		ON	OFF	
★ RS232 A0 Interface		OFF	ON	
ccNet Interface		ON	ON	
ICT104U Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Settings: 2(ccNet)

INTERFACE	SW1	SW2	SW3	SW4
19200 Baud rate	ON			
★ 9600 Baud rate	OFF			
Pulse Interface		ON	OFF	
★ RS232 A0 Interface		OFF	ON	
ccNet Interface		ON	ON	
ICT104U Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Settings: 2(RS232 A0)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
★ Reserved	OFF			
Pulse Interface		ON	OFF	
★ RS232 A0 Interface		OFF	ON	
ccNet Interface		ON	ON	
ICT104U Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

RS232 A0 INFORMATION

Bill Type Data	
Code	Denomination
1	RUB 200
2	RUB 2000
3	RUB 10
4	RUB 50
5	RUB 100
6	RUB 500
7	RUB 1000
8	RUB 5000

Interface Settings: 2(ICT104U)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
★ Reserved	OFF			
Pulse Interface		ON	OFF	
★ RS232 A0 Interface		OFF	ON	
ccNet Interface		ON	ON	
★ ICT104U Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface	Pulse	RS232 A0	ccNet	ICT104U
★ BV1				
BV2	RUB 50	RUB 50	RUB 50	RUB 50
BV3	RUB 100	RUB 100	RUB 100	RUB 100
BV4	RUB 500	RUB 500	RUB 500	RUB 500
BV5	RUB 1000	RUB 1000	RUB 1000	RUB 1000
BV6	RUB 5000	RUB 5000	RUB 5000	RUB 5000
BV7	RUB 200	RUB 200	RUB 200	RUB 200
★ BV8	RUB 2000	RUB 2000	RUB 2000	RUB 2000