

V77E-THB5

V77E Option Switch Settings: 1(Pulse/ICT104U/MDB/ICT104V)

Supported bill ₪ 20, 50, 100, 500, 1000 5bills.

V77E dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject ₪ 20	ON											
★ Accept ₪ 20	OFF											
★ Reject ₪ 50		ON										
★ Accept ₪ 50		OFF										
★ Reject ₪ 100			ON									
★ Accept ₪ 100			OFF									
★ Reject ₪ 500				ON								
★ Accept ₪ 500				OFF								
★ Reject ₪ 1000					ON							
★ Accept ₪ 1000					OFF							
★ High Acceptance (Note.3)						ON						
★ High Security						OFF						
★ BA stops working when fishing							ON					
★ Normal							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / ₪ 10									OFF	OFF		
★ 5 pulses / ₪ 10									ON	OFF		
★ 10 pulses / ₪ 10									OFF	ON		
★ 20 pulses / ₪ 10									ON	ON		
★ Pulse Speed	50ms LO / 50ms HI								OFF	OFF		
	60ms LO / 300ms HI								ON	OFF		
	30ms LO / 50ms HI								OFF	ON		
	150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

Note : (1) Default setting

(2) Use both 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

Appendix

V77E-THB5(Pulse/ICT104U/MDB/ICT104V)

DIP SWITCHES SETTING : 3(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
Pulse Normal Low	OFF			
★ Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
★ ICT104V Interface		ON	ON	
★ MDB Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 3(ICT104U)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
★ Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
★ ICT104V Interface		ON	ON	
★ MDB Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

DIP SWITCHES SETTING : 3(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	OFF			
★ Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0				
★ Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
★ ICT104V Interface		ON	ON	
★ MDB Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	Pulse	MDB	ICT104V
BV1	₪ 20	₪ 20	₪ 20	₪ 20
BV2	₪ 50	₪ 50	₪ 50	₪ 50
BV3	₪ 100	₪ 100	₪ 100	₪ 100
BV4	₪ 500	₪ 500	₪ 500	₪ 500
BV5	₪ 1000	₪ 1000	₪ 1000	₪ 1000

DIP SWITCHES SETTING : 3(ICT104V)

FUNCTION	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
★ Pulse Mode		ON	OFF	
★ ICT104U Interface		OFF	ON	
★ ICT104V Interface		ON	ON	
★ MDB Interface		OFF	OFF	
★ Reserved				ON
				OFF

★ Manufacture setting