

V7E Option Switch Settings: 1(Pulse/CCNet)

Supported bill Ruble 10, 50, 100, 500, 1000 5bills.

V7E dip-switch settings and functions:

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
	Reject Ruble 10	ON											
★	Accept Ruble 10	OFF											
	Reject Ruble 50		ON										
★	Accept Ruble 50		OFF										
	Reject Ruble 100			ON									
★	Accept Ruble 100			OFF									
	Reject Ruble 500				ON								
★	Accept Ruble 500				OFF								
	Reject Ruble 1000					ON							
★	Accept Ruble 1000					OFF							
	Reserved						ON						
★	Reserved						OFF						
	Harness Disable							ON					
★	Harness Enable							OFF					
	Inhibit Active High								ON				
★	Inhibit Active Low								OFF				
★	1 pulse / Ruble 10									OFF	OFF		
	5 pulse / Ruble 10									ON	OFF		
	10 pulse / Ruble 10									OFF	ON		
	20 pulse / Ruble 10									ON	ON		
★	Pulse Speed	50ms on / 50ms off								OFF	OFF		
		60ms on / 300ms off								ON	OFF		
		30ms on / 50ms off								OFF	ON		
		150ms on / 150ms off								ON	ON		

★ Manufacture setting

◆ Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	CCNet Mode		OFF		
★	Reserved			ON	
				OFF	
★					ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 3(CCNet)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	Pulse Mode		ON		
	CCNet Mode		OFF		
★	Baud Rate 19200			ON	
	Baud Rate 9600			OFF	
★	Reserved				ON
					OFF

★ Manufacture setting