

UAH9

L77&L77F DIP SWITCHES SETTING : 1(Pulse/ICT104/ccNet)

Supported bill HRYVEN 1, 2, 5, 10, 20, 50, 100, 200, 500 9bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / HRYVEN 1	OFF	OFF	OFF							
	2 Pulse / HRYVEN 1	OFF	OFF	ON							
	3 Pulse / HRYVEN 1	OFF	ON	OFF							
	4 Pulse / HRYVEN 1	OFF	ON	ON							
	5 Pulse / HRYVEN 1	ON	OFF	OFF							
	10 Pulse / HRYVEN 1	ON	OFF	ON							
	20 Pulse / HRYVEN 1	ON	ON	OFF							
	100 Pulse / HRYVEN 1	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept HRYVEN 1 & 2					ON					
	Reject HRYVEN 1 & 2					OFF					
★	Accept HRYVEN 5 & 10						ON				
	Reject HRYVEN 5 & 10						OFF				
★	Accept HRYVEN 20 & 50							ON			
	Reject HRYVEN 20 & 50							OFF			
★	Accept HRYVEN 100 & 200								ON		
	Reject HRYVEN 100 & 200								OFF		
★	Accept HRYVEN 500									ON	
	Reject HRYVEN 500									OFF	

★ Manufacture setting

Note:(1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip switches 1 to 5 are only for Pulse model.

L77&L77F-UAH9(Pulse/ICT104/ccNet)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	ICT Protocol Mode		ON	ON	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ccNet)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
★	ccNet Mode		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT	Pulse	ccNet
BV1	HRIVEN 1	HRIVEN 1	HRIVEN 1
BV2	HRIVEN 2	HRIVEN 2	HRIVEN 2
BV3	HRIVEN 5	HRIVEN 5	HRIVEN 5
BV4	HRIVEN 10	HRIVEN 10	HRIVEN 10
BV5	HRIVEN 20	HRIVEN 20	HRIVEN 20
BV6	HRIVEN 50	HRIVEN 50	HRIVEN 50
BV7	HRIVEN 100	HRIVEN 100	HRIVEN 100
BV8	HRIVEN 200	HRIVEN 200	HRIVEN 200
BV9	HRIVEN 500	HRIVEN 500	HRIVEN 500