

L77F&PL77-KZT5

L77F&PL77-P3/P6 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill KZT 200, 500, 1000, 2000, 5000 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10	
★	1 Pulse / KZT 100	OFF	OFF	OFF								
	2 Pulse / KZT 100	OFF	OFF	ON								
	3 Pulse / KZT 100	OFF	ON	OFF								
	4 Pulse / KZT 100	OFF	ON	ON								
	5 Pulse / KZT 100	ON	OFF	OFF								
	10 Pulse / KZT 100	ON	OFF	ON								
	20 Pulse / KZT 100	ON	ON	OFF								
	100 Pulse / KZT 100	ON	ON	ON								
	Fast output Pulse Lo= 50ms Hi=100ms				ON							
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF							
	Inhibit level Active Low					ON						
★	Inhibit level Active High					OFF						
★	Accept KZT 200						ON					
	Reject KZT 200						OFF					
★	Accept KZT 500							ON				
	Reject KZT 500							OFF				
★	Accept KZT 1000								ON			
	Reject KZT 1000								OFF			
★	Accept KZT 2000									ON		
	Reject KZT 2000									OFF		
★	Accept KZT 5000										ON	
	Reject KZT 5000										OFF	

★ Manufacture setting

Note:(1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	ICT104U Protocol Mode		OFF		
	Reserved			ON	
★	Reserved			OFF	
	Reserved				ON
★	Reserved				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	ICT
BV1	200	200
BV2	500	500
BV3	1000	1000
BV4	2000	2000
BV5	5000	5000