

L77-CZK6

L77-P3/P6 DIP SWITCHES SETTING : 1(Pulse/ICT104U)

Supported bill CZK 100, 200, 500, 1000, 2000, 5000 6bills.
With stacker : CZK 100, 200, 500, 1000 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10	
★	1 Pulse / CZK 50	OFF	OFF	OFF								
	2 Pulse / CZK 50	OFF	OFF	ON								
	3 Pulse / CZK 50	OFF	ON	OFF								
	4 Pulse / CZK 50	OFF	ON	ON								
	5 Pulse / CZK 50	ON	OFF	OFF								
	10 Pulse / CZK 50	ON	OFF	ON								
	20 Pulse / CZK 50	ON	ON	OFF								
	100 Pulse / CZK 50	ON	ON	ON								
	Fast output Pulse Lo= 50ms Hi=100ms				ON							
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF							
	Inhibit level Active Low				ON							
★	Inhibit level Active High				OFF							
★	Accept CZK 100											ON
	Reject CZK 100					OFF						
★	Accept CZK 200 & 500						ON					
	Reject CZK 200 & 500						OFF					
★	Accept CZK 1000								ON			
	Reject CZK 1000								OFF			
★	Accept CZK 2000									ON		
	Reject CZK 2000									OFF		
★	Accept CZK 5000										ON	
	Reject CZK 5000										OFF	

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	ICT104U Mode		OFF		
★	Reserved			ON	
				OFF	
					ON
					OFF

★ Manufacture setting

Note:(1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

Currency Assign Data

Interface Bill value	Pulse	ICT104U
BV1		
BV2	CZK 100	CZK 100
BV3	CZK 200	CZK 200
BV4	CZK 500	CZK 500
BV5	CZK 1000	CZK 1000
BV6	CZK 2000	CZK 2000
BV7	CZK 5000	CZK 5000