

EUR3+USD3

L77.L77F-P3/P6 DIP SWITCHES SETTING : 1(Pulse/ MDB)

Supported bill € 5, 10, 20
\$ 1, 5, 10

6 bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / € 5 or \$1	OFF	OFF	OFF							
	2 Pulse / € 5 or \$1	OFF	OFF	ON							
	3 Pulse / € 5 or \$1	OFF	ON	OFF							
	4 Pulse / € 5 or \$1	OFF	ON	ON							
	5 Pulse / € 5 or \$1	ON	OFF	OFF							
	10 Pulse / € 5 or \$1	ON	OFF	ON							
	20 Pulse / € 5 or \$1	ON	ON	OFF							
	100 Pulse / € 5 or \$1	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept € 5					ON					
	Reject € 5					OFF					
★	Accept € 10						ON				
	Reject € 10						OFF				
★	Accept € 20							ON			
	Reject € 20							OFF			
★	Accept \$ 1 & 5								ON		
	Reject \$ 1 & 5								OFF		
	Accept \$ 10									ON	
★	Reject \$ 10									OFF	

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

L77.L77F-EUR6-P3/P6(Pulse/MDB)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	MDB Interface		OFF		
★	Reserved			ON	
				OFF	
★					ON
★					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON		
★	MDB Interface		OFF		
★	Reserved			ON	
				OFF	
★					ON
★					OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	Pulse	MDB
BV1	€ 5	€ 5
BV2	€ 10	€ 10
BV3	€ 20	€ 20
BV4	\$ 1	\$ 1
BV5	\$ 5	\$ 5
BV6	\$ 10	\$ 10