

L77&L77F-NZD5

L77&L77F-P3/P6 DIP SWITCHES SETTING : 1(Pulse/ICT)

Supported bill NZD 5, 10, 20, 50, 100 5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / NZD 5	OFF	OFF	OFF							
	2 Pulse / NZD 5	OFF	OFF	ON							
	3 Pulse / NZD 5	OFF	ON	OFF							
	4 Pulse / NZD 5	OFF	ON	ON							
	5 Pulse / NZD 5	ON	OFF	OFF							
	10 Pulse / NZD 5	ON	OFF	ON							
	20 Pulse / NZD 5	ON	ON	OFF							
	100 Pulse / NZD 5	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low				ON						
★	Inhibit level Active High				OFF						
★	Accept NZD 5					ON					
	Reject NZD 5					OFF					
★	Accept NZD 10						ON				
	Reject NZD 10						OFF				
★	Accept NZD 20							ON			
	Reject NZD 20							OFF			
★	Accept NZD 50								ON		
	Reject NZD 50								OFF		
★	Accept NZD 100									ON	
	Reject NZD 100									OFF	

★ Manufacture setting

Note:(1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	ICT104U Interface Mode		OFF		
	Reserved			ON	
★	Reserved			OFF	
	Reserved				
★	Reserved				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT	Pulse
BV1	5	5
BV2	10	10
BV3	20	20
BV4	50	50
BV5	100	100

Appendix