

THB5**L77&L77F-P3/P6 DIP SWITCHES SETTING : 1(Pulse/ICT)**

Supported bill ₪ 20, 50, 100, 500, 1000

5bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / B 10	OFF	OFF	OFF							
	2 Pulse / B 10	OFF	OFF	ON							
	3 Pulse / B 10	OFF	ON	OFF							
	4 Pulse / B 10	OFF	ON	ON							
	5 Pulse / B 10	ON	OFF	OFF							
	10 Pulse / B 10	ON	OFF	ON							
	20 Pulse / B 10	ON	ON	OFF							
	100 Pulse / B 10	ON	ON	ON							
★	Fast output Pulse Lo= 50ms Hi=100ms				ON						
	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept B 20						ON				
	Reject B 20						OFF				
★	Accept B 50							ON			
	Reject B 50							OFF			
★	Accept B 100								ON		
	Reject B 100								OFF		
★	Accept B 500									ON	
	Reject B 500									OFF	
★	Accept B 1000										ON
	Reject B 1000										OFF

★ Manufacture setting

Note:(1)Please reset the bill acceptor after set the dip switch.

(2)Dip switches 1 to 5 are only used for pulse protocol.

DIP SWITCHES SETTING : 2 Currency Assign Data

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High	ON			
	Pulse Normal Low	OFF			
★	Pulse Mode		ON		
	ICT Mode		OFF		
	Reserved			ON	
★	Reserved			OFF	
	Reserved				ON
★	Reserved				OFF

Interface Bill value	ICT	Pulse
BV1	₪ 20	₪ 20
BV2	₪ 50	₪ 50
BV3	₪ 100	₪ 100
BV4	₪ 500	₪ 500
BV5	₪ 1000	₪ 1000

★ Manufacture setting

Appendix