

L77F/PL77-CHF4

L77F&PL77-P3/P6 DIP SWITCHES SETTING : 1(Pulse/ICT104U/MDB)

Supported bill CHF 10, 20, 50, 100 4bills.

	FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / CHF 10	OFF	OFF	OFF							
	2 Pulse / CHF 10	OFF	OFF	ON							
	3 Pulse / CHF 10	OFF	ON	OFF							
	4 Pulse / CHF 10	OFF	ON	ON							
	5 Pulse / CHF 10	ON	OFF	OFF							
	10 Pulse / CHF 10	ON	OFF	ON							
	20 Pulse / CHF 10	ON	ON	OFF							
	100 Pulse / CHF 10	ON	ON	ON							
	Fast output Pulse Lo= 50ms Hi=100ms				ON						
★	Slow output Pulse Lo= 50ms Hi=300ms				OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept CHF 10						ON				
	Reject CHF 10						OFF				
★	Accept CHF 20							ON			
	Reject CHF 20							OFF			
★	Accept CHF 50								ON		
	Reject CHF 50								OFF		
★	Accept CHF 100									ON	
	Reject CHF 100									OFF	
★	Reserve										ON
	Reserve										OFF

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

Currency Assign Data

Interface Bill value	Pulse	ICT104U	MDB
BV1	CHF 10	CHF 10	CHF 10
BV2	CHF 20	CHF 20	CHF 20
BV3	CHF 50	CHF 50	CHF 50
BV4	CHF 100	CHF 100	CHF 100

L77F&PL77-CHF4(Pulse/ICT104U/MDB)

DIP SWITCHES SETTING : 2(Pulse)

	FUNCTION	SW1	SW2	SW3	SW4
★	Credit-Pulse Normal High	ON			
	Credit-Pulse Normal Low	OFF			
★	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(ICT104U)

	FUNCTION	SW1	SW2	SW3	SW4
★	Reserved	ON			
		OFF			
	Pulse Mode		ON	OFF	
★	ICT104U Interface		OFF	ON	
	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting

DIP SWITCHES SETTING : 2(MDB)

	FUNCTION	SW1	SW2	SW3	SW4
★	Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
	Pulse Mode		ON	OFF	
	ICT104U Interface		OFF	ON	
★	MDB Mode		ON	ON	
	Reserved		OFF	OFF	
★	Reserved				ON
					OFF

★ Manufacture setting